

HIOKI

LAN CABLE HiTESTER 3665-20

Optical/Telecom Measurement



***Network Construction with
One Single Instrument***



CAT 6
Compatible

**Shield
Check**

Wiremap

Detect Split Pairs with Wiring Check

Cable Length

Get NVP-Enhanced Measurement Accuracy

Direction

Identify Up to 21 Cable Destinations

Quality Hioki Products Online at:

www.GlobalTestSupply.com

sales@GlobalTestSupply.com

JMI-0216

JQA-E-90091


other information are available on our website.

**Extremely
Intuitive**

Just connect a cable, and
press the TEST button

**Wide
LCD
Screen**

Check all parameters such as wiremap,
direction and cable length at a glance.



1 Wiremap (Wiring Status)

Large PASS/FAIL display, cable type, reason for cable failure and shield condition.

2 Direction (ID No.)

Identify the terminator ID here.

3 Cable Length


Obtain a record of the entire
length of the cable, or up to
the point where the cable is
damaged.

1 Wiremap

For wiring confirmation and locating broken wires after installation. Quick **PASS/FAIL** reading helps you complete your work faster.

PASS Display Examples


Both straight-through and crossover cables (10/100BASE, 1000BASE-T and 1000BASE-TX) can be checked.




**Fully Compatible to
CAT6 LAN Cables**

**Super-
sensitive
Detection**

**Detect the existence of
shields or check for shield integrity.**




FAIL Display Examples




Caution!

Can you find **split pairs?**



PASS Proper Wiring




FAIL Split Pair

2 Direction

Locate up to 21 unique cable destinations.

Have you ever had trouble installing additional cables?



Take advantage of the conveniences offered by the tester's capabilities to check wiring while confirming multiple cable destinations.

Increased Efficiency!

You will never need to go back and forth again just to change the terminators.

Up to 21 terminators can be connected (additional terminators sold separately.) Convenient for confirming the connection destinations of multiple cables.

3 Cable Length

Measure for cable length and detect the location of broken or short-circuited wires.

The NVP* setting is a cable-length compensation function that enhances the accuracy of cable length measurements.

Accuracy with NVP activated:

■ $\pm 4\%$ rdg. $\pm 1\text{m}$

(vs. previous HIOKI model: 15% rdg. $\pm 1\text{m}$)


Increased Precision!



* NVP (Nominal Velocity of Propagation) is the ratio of the speed of a signal in the cable relative to the speed of light in a vacuum.

NVP differs according to the type of cable and the manner in which the wire pairs are twisted, so measurement accuracy can be enhanced by setting the NVP value for the particular type of cable to be measured.

■ Activating the NVP function is as simple as 1-2-3



Preparation

Prepare a reference cable using a known length of the same type as that to be measured (at least 100-meter length recommended).

Measurement
▶Length Adjust
Beep

◀↑↓◀OK NVP 0.684

Adjust ▶101.3m

NVP 0.684

◀↑↓◀OK =Acquire

Adjust ▶100.0m

NVP 0.675

◀↑↓◀OK =Acquire

Adjust ▶OK

Cancel

◀↑↓◀OK

Setting Finished

1

On the Settings screen, select "Length Adjust".

2

Press the TEST button to measure the (already known) length of the reference cable.

3

Calibrate the display to the measured reference cable.

How Can Split Pairs Affect the Network?

- ◆ Communication speed can be suppressed - 100BASE signals may reach only 10BASE speeds.
- ◆ Excessive communication errors - data transfer may be intermittent or completely inhibited.
- ◆ Cables miswired in this way are more susceptible to electrical noise.

Split pairs appear to be properly connected to the untrained eye, and cannot be detected with continuity testing.



To properly check LAN cable wiring, a tester capable of detecting split pairs is indispensable.



The HIOKI 3665-20 can do the job for you properly and

■ Specifications (@ 23 ±5 °C, 80% RH or less, non-condensating, with battery indicator unlit)

Measurable cables	Twisted-pair cable 100 Ω characteristic impedance, shielded and unshielded, CAT 3, 4, 5, 5e and 6
Compatible connectors	RJ-45 plugs
Measurement Items	
[Wiremap]	Wiring condition and shielding can be confirmed using the HIOKI TERMINATOR 9690 Detectable errors: open, short, reversed, transposed, split pairs and other miswiring
[Cable Length]	Measurable lengths: 2 to 300 m, 6.6 to 984 ft Measurement accuracy: ±4% rdg. ±1 m, ±4% rdg. ±3.3 ft Display resolution: 0.1 m
[Destination]	Up to 21 cables can be identified using the supplied TERMINATOR 9690 and optional Models 9690-01 to 9690-04 to test multiple cables simultaneously
Display	128 × 64 dot matrix LCD (with backlight)
Functions	Auto Backlight: pressing a button turns the backlight on (it turns off automatically after about 20 seconds) Beeper: sounds when pressing buttons and when measurement results are displayed Energy-Saving Mode: enter into energy-saving mode after measurement (and resume when the TEST button is pressed) Auto Power Save: the 3665-20 turns off automatically about 10 minutes after the last button press Battery Check: Battery indicator blinks when voltage falls below 2.4 V Unit Switch: Select between meters or feet
Compliance Standards	Safety Standard: EN61010-1:2001 Pollution Level 2 EMC Standard: EN61326:1997 + A1:1998 + A2:2001 + A3:2003
Allowable Input	3.3 V peak (between RJ-45 pins)
Operating Temperature & Humidity	0 to 40 °C, 80% RH or less, non-condensating
Storage Temperature & Humidity	-10 to 50 °C, 80% RH or less, non-condensating
Power Source	Two AA-size (LR6) alkaline batteries
Maximum Power Consumption	1.4 VA
Operating Time	Approx. 50 hours (measuring once per minute)
Size & Weight	Approx. 85 W × 130 H × 33 D mm, approx. 160 g



LAN CABLE HiTESTER 3665-20

(Includes TERMINATOR 9690, CARRYING CASE)

■ Supplied Accessories

TERMINATOR 9690
CARRYING CASE
(Stores the HiTESTER 3665 and TERMINATORs 9690)



TERMINATOR 9690



CARRYING CASE

■ Options

TERMINATOR 9690-01 (IDs 1 to 5)
TERMINATOR 9690-02 (IDs 6 to 10)
TERMINATOR 9690-03 (IDs 11 to 15)
TERMINATOR 9690-04 (IDs 16 to 20)
CARRYING CASE 9249 (stores the 3665-20, 9690 and 9628 together)
LAN CABLE 9628 (1 m long, with RJ-45 plugs)



TERMINATOR 9690-01



CARRYING CASE 9249
(for storing everything together)



LAN CABLE 9628

Note: Company names and Product names appearing in this catalog are trademarks or registered trademarks of various companies.

HIOKI

HIOKI E. E. CORPORATION

HEAD OFFICE :

81 Koizumi, Ueda, Nagano, 386-1192, Japan
TEL +81-268-28-0562 / FAX +81-268-28-0568
http://www.hioki.co.jp / E-mail: os-com@hioki.co.jp

HIOKI (Shanghai) Sales & Trading Co., Ltd. :
1608-1610 Shanghai Times Square Office, 93 Huai Hai Zhong Road,
Shanghai, P.R.China POSTCODE: 200021
TEL +86-21-6391-0090/0092 FAX +86-21-6391-0360
http://www.hioki.cn / E-mail: info-sh@hioki.com.cn
Beijing Office :
TEL +86-10-5867-4080/4081 FAX +86-10-5867-4090
E-mail: info-bj@hioki.com.cn
Guangzhou Office :
TEL +86-20-38392673/2676 FAX +86-20-38392679

DISTRIBUTED BY

Quality Hioki Products Online at:

www.GlobalTestSupply.com

sales@GlobalTestSupply.com

http://www.hiokiusa.com / E-mail: hioki@hiokiusa.com http://www.hioki.in / E-mail: info@hioki.in

All information correct as of Jul. 14, 2010. All specifications are subject to change without notice.

3665E3-07M